

# Control4® Decora Wired Keypad



## Control4® Decora Wired Keypad—C4-KCB

The Control4® Decora Wired Keypad combines beautiful aesthetics and flexible button configuration, providing a stunning user interface that elegantly controls any aspect of a Control4® system. Control lights, scene, music, security—the possibilities are endless. The keypad can be configured with two to seven buttons using four different button sizes for a total of 37 possible configurations. There's no need to worry about how many buttons will be needed on a specific keypad prior to (or even after) installation.

- Includes a button kit with every button necessary to make any of the 37 possible button configurations
- Elegant, sophisticated design makes a beautiful addition to any home or business
- Custom engraving available to clearly identify each button
- Backlit buttons with programmable color control for easy readability regardless of time of day or light level
- Programmable RGB LEDs provide status feedback for lighting and other devices in the system
- Ambient light sensor automatically adjusts backlight and status LED brightness depending on the light level in the room
- Available in a wide array of gloss and satin colors (See Available Colors)
- Control4® screw-less faceplates, sold separately, provide a sleek profile (See Available Accessories)
- RS-485 Bus Communication
- Compatible with the 48V Bus Power Supply

## Control4® Decora Wired Keypad

Model Number	C4-KCB
Programmable Buttons	2-7 depending on configuration
Button LED Feedback	One RGB status LED per button
Power Requirements	48 VDC
Maximum Power Consumption	1.2W
Minimum Power Consumption	0.7W
Recommended Wiring	See "Keypad Bus Wiring Guide" document
<b>Environmental</b>	
Humidity	5% to 95% non-condensing
Storage	-4°F - 158°F (-20°C - 70°C)
Operational Temperature	32°F - 104°F (0°C - 40°C)
<b>Miscellaneous</b>	
Control Communications	RS-485
Weight	0.1lb (0.045kg)
Shipping Weight	0.3lb (0.14kg)
<b>Available Colors</b>	
C4-KCB-xx	WH, LA, IV, BR, BL, SW, MB, BI, AU
<b>Available Accessories</b>	
Faceplate, 1 Gang (C4-FP1-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB
Faceplate, 2 Gang (C4-FP2-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB
Faceplate, 3 Gang (C4-FP3-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB
Faceplate, 4 Gang (C4-FP4-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB
Color Kit (C4-CKK-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU
Engraved Button, Single High (C4-EBD1H-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU
Engraved Button, Double High (C4-EBD2H-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU
Engraved Button, Triple High (C4-EBD3H-xx)	WH, LA, IV, BR, BL, SW, MB, BI, AU

**Gloss Colors:** WH=White, LA=Light Almond, IV=Ivory, BR=Brown, BL=Black

**Satin Colors:** SW=Snow White, MB=Midnight Black, BI=Biscuit, AU=Aluminum

**Metal Finishes:** SN=Satin Nickel, SS=Stainless Steel, VB=Venetian Bronze

**IMPORTANT NOTE:** Requires Bus Ethernet Gateway (C4-DIN-BEG) and Bus Power Supply (C4-DIN-BPS48 or C4-BPS48)

